

Standard electromagnetic ballast for fluorescent applications

BTA EM ballasts for TL Fluorescent lamps

This efficient, reliable, long-life electromagnetic ballast for TL-D fluorescent lamps features a balanced combination of essential characteristics, thus allowing a wide variety of standard applications.

Benefits

- Reliable electrical and mechanical performance
- Compact dimensions
- Electrical design for optimum lamp performance

Features


- Long lifetime
- Quick and easy wiring
- Easy to recognize: blue product label
- Tw marking 130 °C (means average lifetime of 10 years' continuous operation @ 130 °C)
- High-quality screw-in or insert contact

Application

- Retail
- Offices
- Industry
- Home

BTA EM ballasts for TL Fluorescent lamps

Dimensional drawing



Product	D1	C1	C3	A1	A2	A3	A4	B1	B2
BTA 36W 220V C SC	4.0	28.0	1.2	155.0	140.0	48.0	50.0	39.0	20.0
BTA 36W 220V/60Hz C SC	4.0	28.0	1.2	155.0	140.0	48.0	48.0	39.0	20.0

Operating and Electrical

Input Voltage 220 V

Mechanical and Housing

Housing L 155x39x28

Approval and Application

Energy Efficiency Index C

Operating and Electrical

Order Code	Full Product Name	Input Frequency	Line Frequency
913710118443	BTA 36W 220V/60Hz C SC	60 Hz	60 Hz

Order Code	Full Product Name	Input Frequency	Line Frequency
913710119550	BTA 36W 220V C SC	50 Hz	50 Hz

